

SIRKOM

SRK-1080P-E W/3.5G Module

Internet Access via 3.5G HSDPA USB Modem Full HD WMV9 Digital Signage Compatible with Windows Media Player 11 **Supports FTP Auto Download Function Supports HTTP Control Function**

































INTRODUCTION

SIRKOM is pleased to introduce the latest in Digital Signage technology. The SIRKOM SRK-1080P-E is a full-featured digital signage that access to the Internet via 3.5G HSDPA USB Modem anywhere, anytime.

The SIRKOM SRK-1080P-E supports USB port for connecting to the 3G HSDPA USB Modem. With the 3.5G HSDPA USB Modem, the SRK-1080P-E can easily access to the Internet and download the latest demo files automatically. The SIRKOM SRK-1080P-E can be used where there is no wireless infrastructure. For example, it can be installed in vending machine or public transport to introduce products.

The SIRKOM SRK-1080P-E supports high resolution video output such as 1080P / 1080i / 720P for movie theater quality video on a big screen. By connecting to Video, S-Video, Y.Pb.Pr, VGA (resolution up to 1360 x 768), HDMI (1920 x 1080P) and Audio, you can play picture, movie and music on any display device.

FEATURES

- Supports multiple file formats: HD WMV9 and WMA.
- Supports Video, S-Video, Y.Pb.Pr, HDMI, VGA and Audio output.
- HD Y.Pb.Pr output supports resolution: NTSC Mode(60Hz): 480P/720P/1080i.

PAL Mode(50Hz): 576P/720P/1080i.

- HDMI Output: 480P/720P/1080i/1080P.
- VGA output supports resolution: 640x480/800x600/1024x768/1280x1024/1360x768.
- Supports RS-232 port for computer control with ASCII command (play, stop, pause...etc).
- Supports USB port for connecting to the 3.5G HSDPA USB Modem.
- Connect using an Ethernet network cable at up to 100Mbps.
- The source of HD WMV9 MP@HL (Main Profile / High Level) supports resolution up to 1920x1080 (1080P) and the maximum bit rate is 12Mbps.
- Supports CF memory cards. (Suggest using the high speed (150X) CF card)
- Supports HTTP Command function.
- Supports Auto Key Lock function.
- **Exports the Configuration Value:** You can export the configuration value to the CF card. The configuration value can be modified on your PC, and can be applied to the SRK-1080P-E-1 or others.
- Compatible with Windows Media Player 11: Play media files stored in a network computer.
- Supports FTP Auto Download Function: Connect to Remote FTP server and download data to the CF card automatically.
- Supports Download Pause / Resume Function: Continue unfinished downloads upon next session.
- Embedded FTP Server.
- Supports NTP Network (G.M.T) Timer. You can also set the system time manually.
- Supports Universal Plug and Play (UPnP) and DHCP.
- Supports SLIDE SHOW Function (interval time with 10/15/30/60 seconds).

IR Connector (connect to PIR Sensor or IR Cable)

CONNECTION VGA HDM Power **RJ-45 Ethernet** S-Video Connector Connector Switch Connector Connector Y.Pb.Pr DC Input Audio Connector Connector RS-232 Connector Video (for computer control with ASCII command) 'Reset' Connector Button CF READY Empty CF CARD LED PIR Sensor (optional) IR Cable (optional) **CF Card Socket**

APPLICATIONS

The SIRKOM SRK-1080P-E with 3.5G module can be installed in vending machine or public transport, and can auto update the latest demo files anywhere, anytime.

Application 1: Vending Machine



Application 2: Public Transport

